



## AU-ST201CX - 24V DC SINGLE COLOUR FLEXIBLE LED STRIP LIGHT

**PLEASE READ THESE INSTRUCTIONS CAREFULLY BEFORE INSTALLATION  
LEAVE A COPY FOR THE USER / MAINTENANCE ENGINEER FOR FUTURE REFERENCE**

### IMPORTANT INSTALLATION INFORMATION

- Installation should be carried out in accordance with the latest edition of the National Wiring Regulations. If in doubt, consult a qualified electrician.
- The LED Strip operates at **24V DC**.
- AU-DMXCX 3 channel interface is required to operate this strip (please note this not supplied with the strip)
- For use with AU-STCXC wall controller (or suitable DMX controller)

### INSTALLATION INSTRUCTIONS

**Before commencing installation or maintenance, ensure electricity is switched off at the mains.**

1. Connect a suitable 24V DC LED driver to the DC+ and DC- connections on the AU-DMXCX. The strip is 9.8W/m and the choice of LED driver is dependent on the length of strip used. Also refer to the instructions supplied with the LED Driver.
2. Connect the pre-wired tails (+24V, WW and CW ) to the output of the AU-DMXCX interface as shown in Diagram 1
  - +24V to LED +
  - WW to CH1
  - CW to CH2
3. The strip can be cut at a cut-point; there is a cut-point every 50mm.
4. The strip is supplied with a self-adhesive backing which should be applied to clean surfaces.
5. The AU-DMXCX has RJ45 input and output ports to connect into a DMX circuit. See the instruction supplied with the AU-DMXCX for additional information.

### Environmental Protection (W.E.E.E.) – Aurora's WEEE Reg.No. WEE/BG0130YX (UK Only)



Waste Electrical & Electronic Equipment Regulations (WEEE) requires that any of our products showing this marking (left) must not be disposed of with other household or commercial waste. Aurora does not levy any WEEE disposal charges to its customers for affected WEEE related products. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate any such product from other waste types and recycle it responsibly at your local facilities. Check with your Local Authority, Recycling Centre or retailer for recycling advice. If, when you purchased any Aurora product, your supplier included a WEEE disposal fee, you should then contact your supplier for advice on his takeback of the product for the correct disposal.

### Warranty

See [www.auroralighting.com](http://www.auroralighting.com) for full details of warranties and Extended Warranty Terms and Conditions. The warranty is invalid in the case of improper use, tampering, and removal of the Q.C. date label, installation in an improper working environment or installation not according to the current edition of the National Wiring Regulations. Should this product fail during the warranty period it will be replaced free of charge, this is subject to correct installation and return of the faulty product. Aurora does not accept responsibility for any installation costs associated with the replacement of this product. This warranty is in addition to the statutory rights in your country of purchase. Aurora reserves the right to alter specifications without prior notice.

Diagram 1

