



MAINS VOLTAGE SGU10 LOW ENERGY CEILING SPOTLIGHTS



**PLEASE READ THESE INSTRUCTIONS CAREFULLY BEFORE INSTALLATION
LEAVE A COPY FOR THE USER / MAINTENANCE ENGINEER FOR FUTURE REFERENCE**

IMPORTANT INSTALLATION INFORMATION

- Installation should be carried out in accordance with the latest edition of the I.E.E. Wiring Regulations (BS7671). If in doubt, consult a qualified electrician.
- Input voltage - 240V 50Hz AC.
- Use only with SGU10 11W (max) lamp. See product label for lamp type.
- Ensure that ALL electrical connections are tight with no loose strands.
- These luminaires are for indoor use only.
- The nearest illuminated surface must be at least 0.3m from the front of the fitting.
- Suitable for mounting on normally flammable surfaces.

IMPORTANT USER INFORMATION

- Always switch off mains supply before servicing, fitting or changing the lamp.
- Replace failed lamps immediately. Allow the lamp and fitting to cool before replacing lamp.
- Check that the correct lamp type and wattage is fitted (See product label for correct maximum lamp wattage).

INSTALLATION INSTRUCTIONS

1. Switch off the mains supply.
2. Select the required position for the spotlight. Beware of joists, water pipes and electric cables.
3. Remove the base fixing plate from the luminaire.
4. Fix the base plate to the wall/ceiling with the screws and wall plugs provided.
5. Connect the mains supply cable(s) to the terminals and ensure that there are no exposed conductors or trapped insulation:
LIVE – (Red or Brown) to Terminal Marked L
NEUTRAL – (Black or Blue) to Terminal marked N
EARTH – (Green/Yellow) to Terminal marked
6. Secure the luminaire to the base plate.
7. To insert the lamp into the SGU10 lampholder, twist in a clockwise direction. Ensure that the lamp is correctly located in the lampholder.
8. Switch on the power supply.

Environmental Protection (W.E.E.E.) – Aurora's WEEE Reg.No. WEE/BG0130YX



Waste Electrical & Electronic Equipment Regulations (WEEE) requires that any of our products showing this marking (left) must not be disposed of with other household or commercial waste. Aurora does not levy any WEEE disposal charges to its customers for affected WEEE related products. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate any such product from other waste types and recycle it responsibly at your local facilities. Check with your Local Authority, Recycling Centre or retailer for recycling advice. If, when you purchased any Aurora product, your supplier included a WEEE disposal fee, you should then contact your supplier for advice on his takeback of the product for the correct disposal.

GUARANTEE

This product is guaranteed in the UK for a period of 1 year from the date of purchase. The guarantee is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label, installation in an improper working environment or installation not according to the current edition of the I.E.E. Wiring Regulations (BS7671). Should this product fail during the guarantee period it will be replaced free of charge, subject to correct installation and return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product. Your statutory rights are not affected. Aurora reserves the right to alter specifications without prior notice.